

# SVS04-22E VOLTAGE STABILISER

VOLTAGE PROTECTION AND STABILISATION FOR ALL ELECTRICAL AND ELECTRONIC EQUIPMENT

### DESCRIPTION

As both high and low mains voltage can damage your electrical equipment, the Sollatek SVS is designed to monitor and correct the incoming supply continuously.

If the voltage rises or drops, the SVS will stabilise the output to ensure that the voltage reaching your equipment remains constant at 230 V  $(\pm7\%)^*$ . For full input / output voltage profile, please see table in the next page. The Sollatek SVS04-22E has a bright and clear LED display to accurately read the input and output voltage as well as three status LEDs for quick load status indication.

The SVS also protects your electrical equipment against power spikes and surges. Using the SVS ensures a stable, and clean voltage supply to your equipment.

## **APPLICATIONS**

The SVS04-22E is suitable for all electrical and electronic appliances, including: fridges/freezers, vaccine fridges/freezers, medical and laboratory equipment.

#### **FEATURES**

- Microprocessor controlled stabiliser
- Solid state with no moving parts
- Requires no maintenance
- Extremely fast response
- Excellent output voltage stability
- Very wide input voltage range (110 287 V)
- Includes surge and spike suppression and protection
- Incorporates over & under voltage disconnect (AVS™ function) when mains is extreme and outside working limits
- 6 Minute startup delay as standard to allow neutralisation of compressor gases, critical in such applications (10 second model also available)
- Incorporates TIMESAVE™ Function (10 second start-up delay after long duration powercut)
- Frequency/Voltage measurement smoothing via software to filter noise
- Compact modern design incorporating lightweight, high grade flame retardant ABS
- Modern 7 segment LED display for input & output voltage and 3 status LED indicators
- British design



Actual unit may differ from shown

## FEATURES



# **PROTECTION AGAINST**



#### **PROTECTION FOR**




# 😵 Voltright

\* For input voltage between 125 V to 280 V

INPUT & OUTPU	Л							INPUT	OUTPUT	
Input Range			110 V to 287 V					0-105	OFF	
Output Range			202 V to 245 V				110	200/OFF		
Input Operating Range	Over Voltage	Disconnect	287 V					115	209	
		Reconnect	285 V					120	218	
	Under Voltage	Disconnect	110 V					125	227	
		Reconnect	116 V					130	236	
Load Current			4 A					135	210	
Frequency Range			35 Hz to 65 Hz					140	217	
GENERAL								145	225	
Derating Factor			10% to 15% per 10°C above 40°C					150	233	
Synchronization			Output synchronized to input					155	249/211	
Permissible Overload			Overload 1000% for 100ms, 720% for 10 seconds, 150% for 120 seconds					160	218	
Load Types			Fridges, Freezers, Medical Cold Chain (vaccine fridges/ freezers), Laboratory and Medical Equipment, Computers, IT Equipment					165	225	
								170	232	
Technology			Transformer tap switching using relays					175	238	
			88% at 25% load, 94% at 50% load, 96% at 75% load,					180	209	
Efficiency			97% at 100% load					185	215	
Control			Microcontroller based control system provides self checks,					190	221	
			system integrity, monitoring and diagnostic indicators Internal surge arrestors and filters in control circuit protect					195	227	
Control Protection			against disturbances. Filtering algorithms and fault tolerant software protect against disturbances and false measurements					200	233	
							ents	205	239	
Ambient Temp Range			-30°C to +70°C when product is inactive -5°C to +55°C during use					210	243/210	
Relative Humidity			< 95%, non condensing					215	215	
Acoustic Noise			< 45 dB (A)					220	220	
Expected Service Life			> 10 years					225	225	
			Manufactured to comply with:					230	230	
Standards			ISO9001:2000, CE, EN 50081-1:1992, EN 50082-1:1998, EN 55022:1998, EN 61000-4-2:1995/1998, EN 61000-4-3:1996, EN 61000-4-4:1995, EN 61000-4-5:1995, EN 61000-4-6:1996, EN 61000-4-11:1994, DD ENV 50204, BS EN 61558-1, EN 60065,				NI	235	235	
								240	240	
							,	245	245/209	
Correction Speed			EN 60555 750 Volts per second					250	214	
Response			Within 0.1 second					255	218	
Wait Time on Start Up			10 sec or 6 minutes (depending on model)					260	222	
Power Factors			Unaffected by load power factor					265	226	
AVS™ Function TimeSave™ Function			Automatic voltage switcher: output is switched off to protect				ct	270	231	
			device against over and under voltage and automatically reconnects when safe					275 280	235 239	
			Reduced startup delay if unit was off for more than the standard delay period to 10 seconds					285	243	
MECHANICAL								290	OFF	
Connection Plug and Socket								All weights and dimensions are		
Unit Dimension WxHxD			161 x 131 x 277 mm 7.2 kg				All weights and dimensions are approximate. Specifications are subject to change without prior			
Carton Dimensions WxHxD			290 x 180 x 550 mm				2	notice. ©Sollatek (UK) Limited 2024. All Rights Reserved.		
Pallet Dimensions WxHxD			1000 x 1100 x 1200 mm	ineight	OTV					
rallet Dimension	S VVXHXD		1000 X 1100 X 1200 mm		441.0 kg		50			

**VOLTAGE TABLE** 


**TECHNICAL SPECIFICATION** 



The diagrams presented are for illustrative purposes only. Detailed drawings are available upon request.

#### **REAR PANEL DIAGRAM**

i



Alternative plug types available: Type B, C, D, G, I and M. Other plug types not listed available upon request.

# PRODUCT CODE DESCRIPTION

 98204E16
 SVS04-22E 4A 1kVA 110-285V 6min Euro

 98204E16-10
 SVS04-22E 4A 1kVA 110-285V 10sec Euro

#### SOLLATEK (UK) LIMITED

Sollatek House, Waterside Drive, Langley, Slough SL3 6EZ, United Kingdom

Tel: +44 (1753) 214 500 Email: sales@sollatek.com Web: www.sollatek.com ISO9001: 2015 accredited company All weights and dimensions are approximate. Specifications are subject to change without prior notice. @Sollatek (UK) Limited 2024. All Rights Reserved. SOLLATEK and the SOLLATEK device are the trade marks of the Sollatek group of companies.

# - 3